



R400 Ruthenium Oxide Standard Curve

	Temp (K)	LogOhms		Temp (K)	LogOhms		Temp (K)	LogOhms
1	2.00	5.362387	19	20.00	5.115958	38	39.00	5.066414
2	3.00	5.331990	20	21.00	5.111658	39	40.00	5.064900
3	4.00	5.302156	21	22.00	5.107661	40	50.00	5.052559
4	5.00	5.275550	22	23.00	5.103934	41	60.00	5.043736
5	6.00	5.252760	23	24.00	5.100453	42	70.00	5.037085
6	7.00	5.233223	24	25.00	5.097197	43	77.00	5.033283
7	8.00	5.216404	25	26.00	5.094139	44	80.00	5.031797
8	9.00	5.201824	26	27.00	5.091266	45	90.00	5.027447
9	10.00	5.189123	27	28.00	5.088556	46	100.00	5.023865
10	11.00	5.177895	28	29.00	5.085998	47	125.00	5.017022
11	12.00	5.167900	29	30.00	5.083575	48	150.00	5.012113
12	13.00	5.158955	30	31.00	5.081278	49	175.00	5.008459
13	14.00	5.150929	31	32.00	5.079095	50	200.00	5.005774
14	15.00	5.143683	32	33.00	5.077019	51	225.00	5.003798
15	16.00	5.137107	33	34.00	5.075042	52	250.00	5.002430
16	17.00	5.131124	34	35.00	5.073158	53	270.00	5.001677
17	18.00	5.125643	35	36.00	5.071358	54	273.00	5.001587
18	19.00	5.120602	36	37.00	5.069638			
			37	38.00	5.067991			

Cryogenic Control Systems, Inc.
PO Box 7012
Rancho Santa Fe, CA 92067

T: 858-756-3900 F: 858-759-3515
E: sales@cryocon.com
W: www.cryocon.com